



Installation Guide for the

AV Bridge MatrixMIX

Multipurpose AV Switcher

Document 411-0006-31 Rev A
August 2017

Contents

Overview	1
What's in this Guide	1
Features	1
Product Compatibility	2
Control Devices	2
Vaddio Cameras	2
Non-Vaddio Cameras	2
Unpacking the Switcher	3
A Quick Look at the Switcher	4
Status lights	4
Connector Panel	4
Installation	5
Don't Void Your Warranty!	5
Cabling Notes	5
Basic Connections	6
Powering Up	6
Next Steps	6
Troubleshooting	7
Operation, Storage, and Care	7
Compliance Statements and Declarations of Conformity	8
FCC Part 15 Compliance	8
ICES-003 Compliance	8
European Compliance	9
Warranty Information	10
Photo Credits	11
Index	12

Overview

This guide provides information about the AV Bridge MatrixMIX multipurpose AV switcher:

- 999-5660-000 – North America
- 999-5660-001 – Europe and UK
- 999-5660-009 – Australia and New Zealand



What's in this Guide

This guide covers:

- Unpacking the AV switcher
- Tips for a successful installation
- Information on connecting the AV switcher
- Equipment power-on

Complete product information is available in the **Integrator's Complete Guide to the AV Bridge MatrixMIX Multipurpose AV Switcher**.

Features

Operator-friendly:

- IP connectivity to controllers for virtualized control across the network
- Intuitive, visually consistent interfaces – web interface or connected TeleTouch Multiviewer
- Basic configuration tasks available from the front panel
- Separate outputs for program, preview, and multiview

Versatile connectivity:

- RS-232 ports for 6 cameras
- HDMI inputs with embedded audio support - video from 6 cameras and 2 additional video sources
- Audio: 2 microphone/line inputs and 2 line outputs
- USB 3.0 port for uncompressed AV streaming, USB 2.0 ports for control (touch-panel or pointing device)
- Network connection for IP H.264 streaming and virtualized control from anywhere

Professional results:

- PIP functions; graphics functions including keys, digital on-screen graphics, and banners
- Automatic echo cancellation and speech lift for crystal-clear audio
- Simultaneous USB and IP streaming outputs

Product Compatibility

The AV Bridge MatrixMIX is compatible with the following products.

Control Devices

- PCC MatrixMIX live production controller
- PCC Premier precision camera controller
- TeleTouch 27 USB touch-screen multiview display

Vaddio Cameras

May require an update to the camera's firmware.

* Includes cameras marked ClearSHOT 10 USB.

Product	RS-232	IP
RoboSHOT Series (may use Quick-Connect or OneLINK device)	Yes	Yes**
ConferenceSHOT Series*	Yes	Yes
ClearVIEW HD 20SE	Yes	No
PowerVIEW HD 22/30	Yes	No
ZoomSHOT 20	Yes	No
WideSHOT	Yes	No

** If the camera is connected via a Quick-Connect or OneLINK device, IP control uses the camera's IP address, not the address of its extension device.

Non-Vaddio Cameras

Product	RS-232	IP
Sony BRC Z330, Z700, H700, H900	Yes	No
Sony EVI-H100S	Yes	No
Sony SRG 120, SRG 300	Yes	No
Panasonic AW-HE 40, AW-HE 130	Yes	No

Unpacking the Switcher

Make sure you received all the items you expected. Here are the packing lists for the AV Bridge MatrixMIX multipurpose AV switcher.

North America: AV Bridge MatrixMIX, part number 999-5660-000

- AV Bridge MatrixMIX, part number 998-5660-000
- Power supply with US cord set
- Quick Start Guide, part number 411-0006-00

International: AV Bridge MatrixMIX, part number 999-5660-001

- AV Bridge MatrixMIX, part number 998-5660-000
- Power supply with Euro and UK cord sets
- Quick Start Guide, part number 411-0006-00

Australia: AV Bridge MatrixMIX, part number 999-5660-009

- AV Bridge MatrixMIX, part number 998-5660-000
- Power supply with Australia/New Zealand cord set
- Quick Start Guide, part number 411-0006-00



A Quick Look at the Switcher



- 8-line illuminated display – View basic operation and configuration menu and system information
- Menu knob – Navigate the operation/configuration menu
- Select and Cancel buttons – Work with the operation/configuration menu
- Program and Preview buttons 1 through 8 – Select the program and preview sources
- Take button – Transition from the program source to the preview source, or vice-versa
- USB 2.0 ports, front and back: Control (TeleTouch 27 USB or pointing device)

Status lights

The Program and Preview buttons illuminate to indicate status:

- Red – Program video source (tally, "on-air")
- Green – Preview video source (next input to take)
- Blue – The video source is connected and in communication with the switcher
- Blinking blue – The video source cannot be detected by the chosen configuration of that camera control
- Not illuminated – No video source is connected

Connector Panel



Connections, left to right, by row:

- External Control: RS-232 port for external control device; trigger inputs for up to 10 presenter-controlled devices
- RS-232 Ports (Camera 1 - Camera 6): Camera control connections
- Audio I/O: Connections for 2 microphones (or other line inputs) and 2 line outputs
- 12 VDC 5.0 Amp: Power connection
- Network: Control, IP streaming, graphics
- USB 3.0: Uncompressed audio and video stream
- USB 2.0 ports, front and back: Control (TeleTouch 27 USB or pointing device)
- HDMI Inputs: Video from connected cameras and other video sources; HDCP support
- HDMI Outputs: Program, preview, and multiview; audio on program and preview

Installation

This section covers how to install and connect the product. It also provides safety information and other guidance related to installing the product.

Note

This product is intended for installation and use only in environments where all RS-232 and PoE+ connections originate within the building.

Don't Void Your Warranty!

Caution

This product is for indoor use. Do not install it outdoors or in a humid environment without the appropriate protective enclosure. Do not allow it to come into contact with any liquid.

Do not install or operate this product if it has been dropped, damaged, or exposed to liquids. If any of these things happen, return it to Vaddio for safety and functional testing.

Learn more at www.vaddio.com/products.

Cabling Notes

Use Cat-5e or better cable and standard RJ-45 connectors (568B termination). We recommend using high-quality connectors and a high-quality crimping tool.


RS-232 cables may be up to 500 ft (152.4 m).

Note

Use standard RJ-45 connectors and a good crimping tool. Do not use pass-through RJ-45 connectors. Poorly crimped connectors can damage the connectors on the product, cause intermittent connections, and degrade signal quality. Test cable pin-outs and continuity before connecting them.



Intact – Contact fingers will make reliable contact with the cable connector



Damaged – Some contact fingers are bent and will NOT make reliable contact with the cable connector

Caution

Check Cat-5 cables for continuity before using them. Using the wrong pin-out may damage the camera system and void the warranty.



Pro Tip

To prevent tragic mishaps, label both ends of every cable.

Basic Connections

The diagram below shows a basic live production setup.



Powering Up

1. Power up all the cameras to be used.
2. Connect the power supply.
3. Power up the camera controller, if your setup includes one.

Next Steps

The AV Bridge MatrixMIX is now ready to configure. This includes setting up its address book to manage cameras via the IP network. Until the product is fully configured, its full functionality is not available. This information is available in the **Configuration and Administration Guide for the AV Bridge MatrixMIX**. It is also covered in the **Integrator's Complete Guide to the AV Bridge MatrixMIX**.

Download manuals, dimensional drawings, and other information from www.vaddio.com/support.

Troubleshooting

If the equipment does not power up as expected, use this table to determine whether to call Vaddio Technical Support.

What is it doing?	Possible causes	Check and correct
Nothing. The display is off and the buttons do not light up.	Power is not connected.	Connect the mid-span power injector's power cord.
	The network/PoE+ cable from the mid-span power injector is bad.	Check using known good cables.
	The wall outlet is not active. (Check by finding out if it powers something else, such as a laptop or phone charger.)	Use a different outlet.
	The device or its mid-span power injector is bad.	Contact your reseller or Vaddio Technical Support.

Operation, Storage, and Care

For smears or smudges on the product, wipe with a clean, soft cloth. Do not use any abrasive chemicals.

Keep this device away from food and liquids.

Do not operate or store the device under any of the following conditions:

- Temperatures above 40°C (104°F) or below 0°C (32°F)
- High humidity, condensing or wet environments
- Inclement weather
- Severe vibration
- Dry environments with an excess of static discharge

Do not attempt to take this product apart. There are no user-serviceable components inside.

Compliance Statements and Declarations of Conformity

Compliance testing was performed to the following regulations:

FCC Part 15 (15.107, 15.109), Subpart B	Class A
ICES-003, Issue 54: 2012	Class A
EMC Directive 2004/108/EC	Class A
EN 55032: 2015	Class A
EN 55024: November 2010	Class A
KN22 2008 (CISPR 22: 2006)	Class A
KN24 2008 (CISPR 24: 1997 + A1: 2000 + A2: 2002)	Class A
IEC 60950-1:2005 (2nd Edition); Am 1: 2009 + Am 2: 2013	Safety
EN 60950-1: 2006 + A11: 2009 + A1: 2010 + A12: 2011 + A2: 2013	Safety

FCC Part 15 Compliance

This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to Part 15, Subpart B, of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at his/her own expense.

Operation is subject to the following two conditions: (1) This device may not cause interference, and (2) This device must accept any interference including interference that may cause undesired operation of the device.



Changes or modifications not expressly approved by Vaddio can affect emission compliance and could void the user's authority to operate this equipment.

ICES-003 Compliance

This digital apparatus does not exceed the Class A limits for radio noise emissions from digital apparatus set out in the Radio Interference Regulations of the Canadian Department of Communications.

Le présent appareil numérique n'émet pas de bruits radioélectriques dépassant les limites applicables aux appareils numériques de la classe A prescrites dans le Règlement sur le brouillage radioélectrique édicté par le ministère des Communications du Canada.



European Compliance

This product has been evaluated for Electromagnetic Compatibility under the EMC Directive for Emissions and Immunity and meets the requirements for a Class A digital device. In a domestic environment this product may cause radio interference in which case the user may be required to take adequate measures.

Standard(s) To Which Conformity Is Declared:



EMC Directive 2004/108/EC

EN 55022: December 2010

EN 55024: November 2010

EN 61000-4-2: 1995 + Amendments A1: 1998 + A2: 2001

EN 61000-4-3: 2006 + A1: 2008

EN 61000-4-4: 2004 + Corrigendum 2006

EN 61000-4-5: 2006

EN 61000-4-6: 2009

EN 61000-4-8: 2010

EN 61000-4-11: 2004

KN22 2008 (CISPR 22: 2006)

KN24 2008 (CISPR 24: 1997 + A1: 2000 + A2: 2002)

EN 61000-4-2

EN 61000-4-3

EN 61000-4-4

EN 61000-4-5

EN 61000-4-6

EN 61000-4-8

EN 61000-4-11

IEC 60950-1: 2005 (2nd Edition); Am 1: 2009 + Am 2: 2013

EN 60950-1: 2006 + A11: 2009 + A1: 2010 + A12: 2011 + A2: 2013

Conducted and Radiated Emissions

Immunity

Electrostatic Discharge

Radiated Immunity

Electrical Fast Transients

Surge Immunity

Conducted Immunity

Power Frequency Magnetic Field

Voltage Dips, Interrupts and
Fluctuations

Conducted and Radiated Emissions

IT Immunity Characteristics

Electrostatic Discharge

Radiated Immunity

Electrical Fast Transients

Surge Immunity

Conducted Immunity

Power Frequency Magnetic Field

Voltage Dips, Interrupts and
Fluctuations

Safety

Safety

Warranty Information

See Vaddio Warranty, Service and Return Policies posted on support.vaddio.com for complete details.

Hardware* warranty: Two (2) year limited warranty on all parts and labor for Vaddio manufactured products. Vaddio warrants its manufactured products against defects in materials and workmanship for a period of two years from the day of purchase, to the original purchaser, if Vaddio receives notice of such defects during the warranty. Vaddio, at its option, will repair or replace products that prove to be defective. Vaddio manufactures its hardware products from parts and components that are new or equivalent to new in accordance with industry standard practices.

Exclusions: The above warranty shall not apply to defects resulting from improper or inadequate maintenance by the customer, customers applied software or interfacing, unauthorized modifications or misuse, mishandling, operation outside the normal environmental specifications for the product, use of the incorrect power supply, modified power supply or improper site operation and maintenance. OEM and special order products manufactured by other companies are excluded and are covered by the manufacturer's warranty.

Vaddio Service Department: Vaddio will test, repair, or replace the product or products without charge if the unit is under warranty. If the product is out of warranty, Vaddio will test then repair the product or products. The cost of parts and labor charge will be estimated by a technician and confirmed by the customer prior to repair. All components must be returned for testing as a complete unit. Vaddio will not accept responsibility for shipment after it has left the premises.

Vaddio Technical Support: Vaddio technicians will determine and discuss with the customer the criteria for repair costs and/or replacement. Vaddio Technical Support can be contacted by email at support@vaddio.com or by phone at one of the phone numbers listed on support.vaddio.com.

Return Material Authorization (RMA) number: Before returning a product for repair or replacement request an RMA from Vaddio's technical support. Provide the technician with a return phone number, e-mail address, shipping address, product serial numbers and original purchase order number. Describe the reason for repairs or returns as well as the date of purchase. See the General RMA Terms and Procedures section for more information. RMAs are valid for 30 days and will be issued to Vaddio dealers only. End users must return products through Vaddio dealers. Include the assigned RMA number in all correspondence with Vaddio. Write the assigned RMA number clearly on the shipping label of the box when returning the product. All products returned for credit are subject to a restocking charge. Special order product are non-cancelable and not returnable.

Voided warranty: The warranty does not apply if the original serial number has been removed or if the product has been disassembled or damaged through misuse, accident, modifications, use of incorrect power supply, use of a modified power supply or unauthorized repair.

Shipping and handling: Vaddio will not pay for inbound shipping transportation or insurance charges or accept any responsibility for laws and ordinances from inbound transit. Vaddio will pay for outbound shipping, transportation, and insurance charges for all items under warranty but will not assume responsibility for loss and/or damage by the outbound freight carrier. If the return shipment appears damaged, retain the original boxes and packing material for inspection by the carrier. Contact your carrier immediately.

Products not under warranty: Payment arrangements are required before outbound shipment for all out of warranty products.

Photo Credits

European Space Agency (ESA) astronaut Samantha Cristoforetti, a Flight Engineer with Expedition 42, photographs the Earth through a window in the Cupola on the International Space Station

By NASA - https://blogs.nasa.gov/ISS_Science_Blog/2015/03/06/women-in-space-part-two-whats-gender-got-to-do-with-it/, Public Domain, <https://commons.wikimedia.org/w/index.php?curid=38834990>

Carl Sagan, Bruce Murray, Louis Friedman (founders) and Harry Ashmore (advisor), on the occasion of signing the papers formally incorporating The Planetary Society

By credit NASA JPL - JPL, Public Domain, <https://commons.wikimedia.org/w/index.php?curid=1180927>

Main Control Room / Mission Control Room of ESA at the European Space Operations Centre (ESOC) in Darmstadt, Germany

By European Space Agency - ESOC flickr, Credit: ESA - Jürgen Mai, CC BY-SA 3.0-igo, <https://commons.wikimedia.org/w/index.php?curid=36743173>

Expedition 42 on orbit crew portrait, International Space Station, Mar. 7, 2015 – Barry Wilmore (Commander) Top, Upside down, to the right cosmonaut Elena Serova, & ESA European Space Agency Samantha Cristoforetti. Bottom center US astronaut Terry Virts, top left cosmonauts Alexander Samokutyaev and Anton Shkaplerov.

By NASA - <https://www.flickr.com/photos/nasa2explore/16166230844/>, Public Domain, <https://commons.wikimedia.org/w/index.php?curid=38931301>

European Space Agency astronaut Luca Parmitano, Expedition 36 flight engineer, outside the International Space Station

By NASA - <http://spaceflight.nasa.gov/gallery/images/station/crew-36/html/iss036e016704.html>, Public Domain, <https://commons.wikimedia.org/w/index.php?curid=27263573>

Chris Cassidy, Luca Parmitano, and Karen Nyberg, ISS, 2013. Photo Credit: NASA

Nicolas Altobelli, Rosetta Scientist at ESA's European Space Astronomy Centre, Villanueva de la Cañada, Madrid, Spain

By European Space Agency - Nicolas Altobelli talks to the media, CC BY-SA 3.0-igo, <https://commons.wikimedia.org/w/index.php?curid=36743144>

Andrea Accomazzo, ESA Rosetta Spacecraft Operations Manager, providing a live update from the Main Control Room at ESA's European Space Operations Centre, Darmstadt, Germany during the Rosetta wake-up day.

By European Space Agency - Live update from the Main Control Room, CC BY-SA 3.0-igo, <https://commons.wikimedia.org/w/index.php?curid=36743150>

Index

A

- accessories 3
- audio 4
 - connections 4

B

- buttons 4
 - camera select 4
 - Take 4

C

- cable 5
 - connectors 5
 - length, maximum 5
- camera select buttons 4
- camera status indicators 4
- capabilities 1
- cleaning 7
- compatibility 2
 - hardware 2
- connection diagram 6
- connector panel 4

D

- damage, preventing 5
- diagram, connection 6
- display, front panel 4

F

- front panel display 4

H

- hardware setup 6
- HDMI connections 4

I

- indicator lights 4

M

- maximum cable lengths 5
- menu knob 4

O

- operating environment 7
- other information resources 6

P

- packing list 3
- part numbers 3
- power-up order 6
- product capabilities 1
- product returns and repairs 10

R

- RJ-45 connectors 5
- RS-232 4
 - ports 4

S

- storage environment 7

T

- Take button 4
- temperature, operating and storage 7
- trigger input connections 4

U

- USB connections 4

W

- warranty 5, 10
- what's in the box 3

Vaddio is a brand of Milestone AV Technologies · www.vaddio.com · Phone 800.572.2011 / +1.763.971.4400 · Fax +1.763.971.4464 · Email info@vaddio.com

Visit us at support.vaddio.com for firmware updates, specifications, drawings, manuals, technical support information, and more.

Vaddio, AV Bridge, and MatrixMIX are trademarks or registered trademarks of Milestone AV Technologies. The term HDMI and the HDMI logo are trademarks or registered trademarks of HDMI Licensing LLC in the United States and other countries. All other brand names or marks are used for identification purposes and are trademarks of their respective owners.

In British Columbia, Milestone AV Technologies ULC carries on business as MAVT Milestone AV Technologies ULC.

©2017 Milestone AV Technologies

The logo for Vaddio, featuring the word "vaddio" in a bold, blue, lowercase sans-serif font. The final letter "o" is stylized as a blue circle with a smaller blue circle inside it, resembling an eye or a camera lens. A registered trademark symbol (®) is located at the top right of the "o".

vaddio®