

eSAM702

ANALOGUE PREAMPLIFIERS & MIXERS

Installation Analogue Mixer



PRODUCT OVERVIEW

eSAM702 is an installation audio mixer in standard rack format, featuring 6 MIC/LINE ST inputs, 1 LINE ST input, 1 main mix output and one AUX/REC additional output. It includes a 3 band tone control section, Talkover (priority) function assignable to each MIC/LINE input over the mix bus, ST/MONO mix switch and MUTE port for external dry contact triggering.

KEY FEATURES

- 7 input channels, 2 outputs 19" installation mixer
- 6 MIC/LINE ST inputs
- 1 LINE ST input
- 1 main mix output and one AUX/REC additional output
- 3 band tone control section
- Talkover (priority) function assignable from each MIC/LINE input over the mix
- Micro sensitivity level can be adjusted on the back panel
- +18V Phantom Power available for all MIC inputs
- Universal external power supply (multi-plug)

APPLICATIONS

- Gyms
- Licensed venues
- Restaurants
- Leisure venues
- Retail shops
- Boardrooms and conference centres
- Entertainment music playback
- Education centres
- A/V presentations

TECHNICAL SPECIFICATIONS






eSAM702

Inputs Sensitivity (*) / Impedance		
	LINE (1-6)	0dBV / 50k Ω
	LINE 7	-6dBV* / 50k Ω
Input sensitivity adjust		
	MIC 1-6 BAL	35dBV/>1k Ω
	MIC/LIN 1-6	\pm 15dB
Outputs Level / Minimum load		
	OUT	0(+6)dBV* / 600 Ω
	AUX/REC	0dBV/10k Ω
Frequency response		
	LINE	10Hz-50kHz - 1dB
	MIC BAL	10Hz-30kHz - 1dB
Harmonic distortion		
	LINE	<0.005%dB
	MIC BAL	<0.04%dB
CMRR		
	MIC	>60dB@1kHz
Signal / Noise ratio		
	LINE	>110dB
	MIC BAL	>85dB
Tone control		
	BASS	100Hz \pm 15dB
	MID	2kHz \pm 15dB
	TREBLE	10kHz \pm 15dB
Talkover		
	TIME	2 sec.
	EFFECT	-30dB
Phantom voltage		
		+18VDC
DC supply		
		\pm 17,5 VDC
Mains		
		100-240VAC + External PSU 17,5VDC
Power consumption		
		16VA
Dimensions		
	Panel	482,6x44mm
	Depth	120mm
Weight		
		1,8kg

*internally selectable

MECHANICAL DIAGRAM

Measurements indicated in mm.





All product characteristics are subject to variation due to production tolerances. **NEEC AUDIO BARCELONA S.L.** reserves the right to make changes or improvements in the design or manufacturing that may affect these product specifications

For technical queries contact your supplier, distributor or complete the contact form on our website, in [Support / Technical requests](#).

Motors, 166-168 - 08038 Barcelona - Spain - (+34) 932238403 | information@ecler.com | www.ecler.com